


EVRF

EndoVenous Radio Frequency

Quick User Guide


For more detailed information please consult the manual



1. Display with touchscreen.
2. Connection for the 3M Cable.(black)
3. Connection for the footswitch.(blue)
4. Connection for the needle holder pen and catheter.(red)

Use of the EVRF

- ① Connect the footswitch to the apparatus (blue plug).
- ① Switch on the apparatus, the welcome screen appears.
- ① The program selection screen is shown.



WARNING! Patient may not be grounded or connected to any other radiofrequency device!

Parameters for treatment of varicose veins and hemorrhoids:

EVRF settings for the transcutaneous treatment

Diameter vein	0,3 - 0,6 mm	0,7 - 1 mm
Treatment area	Face	Leg
Needle	K3i	K6i
Power (watt)	5 - 8 Max. 10	9 - 14 Max. 16
Impulse time	0,2 - 0,3 s	0,3 - 0,4 s Max 0,5s
Connection of pad required	NO	NO

EVRF settings for the CR30KAB catheter

Diameter vein	2 - 5mm
Catheter	CR30KAB
Needle	G20 needle
Power (watt)	15
Continuous mode	Keep footswitch pressed down
Number beeps at start	3
Number beeps per 0,8cm retraction	3
Connection of pad required	Optional

EVRF settings for the CR45i catheter

Diameter vein	6 - 18 mm
Catheter	CR45i
Needle	6 French Introducer
Power (watt)	25
Continuous mode	Keep footswitch pressed down
Number beeps at start	2 x 3
Number beeps per 0,5 cm retraction	3
Connection of pad required	YES

EVRF settings for the HPR45i probe

Hemorrhoids	Degree II, III, IV
Probe	HPR45i
Power (watt)	25
Continuous mode	Keep footswitch pressed down
Connection of pad required	NO

www.fcaresystems.com - Tel: +32 3 451 51 45